

TITLE OF THE INVENTION

ELECTRONIC APPARATUS

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is based upon and claims the
5 benefit of priority from the prior Japanese Patent
Application No. 2000-157015, filed May 26, 2000,
the entire contents of which are incorporated herein
by reference.

BACKGROUND OF THE INVENTION

10 The present invention relates to an electronic
apparatus, and more particularly, to an electronic
apparatus capable of radio data communication with
some other electronic apparatuses using a radio
communication card.

15 When a personal computer is used for internet
connection, in general, a modem that is attached to the
computer and a modular jack of a public data network in
a general home are connected to each other by means of
a modular cable. When using this modular cable,
20 however, the connection and wire arrangement are
troublesome. If the personal computer and the modular
jack are remote from each other, they cannot be
connected with ease. Accordingly, the place of
installation of the personal computer cannot be
25 selected freely.

This problem of connection can be solved by
a current prevailing radio communication connecting

apparatus that utilizes radio communication for connection without using any modular cable. This radio communication connecting apparatus is connected to the public data network by means of a modular cable, and data are transmitted between the personal computer and the connecting apparatus by radio communication, whereby the computer and the network are connected to each other. With use of this connecting apparatus, troublesome connection and arrangement of the modular cable can be eliminated, the place of installation of the personal computer can be selected freely, and the range of service can be extended.

In some cases, however, the radio communication connecting apparatus of this type may not be able to be used, depending on various conditions, such as the function and design, the type of the corresponding personal computer, OS, and line, expansibility, etc. that vary according to products.

BRIEF SUMMARY OF THE INVENTION

Accordingly, the object of the present invention is to provide a highly versatile electronic apparatus, capable of radio communication with some other electronic apparatuses using a radio communication card and of being wirelessly connected or linked to various apparatuses with ease.

In order to achieve the above object, an electronic apparatus according to the present invention

comprises: a holding portion for detachably holding
a radio communication card including an antenna;
a metal plate on which the holding portion is provided;
and a connecting portion for data communication with
5 the radio communication card held by the holding
portion. The holding portion is arranged to hold the
radio communication card in a manner such that the
antenna is exposed outside of the holding portion and
the minimum distance between the antenna and the metal
10 plate is 1 mm or more.

According to the electronic apparatus constructed
in this manner, the radio communication card can be
used for radio communication between some electronic
apparatuses. This electronic apparatus is a highly
15 versatile apparatus that can be wirelessly connected or
linked to various other apparatuses with ease.
Further, the distance between the antenna and an end
portion of a metal plate of the apparatus body is 1 mm
or more, and preferably, 2 mm or more. In this case,
20 the metal plate can be prevented from intercepting or
attenuating the radio waves, so that steady data
communication can be ensured.

An electronic apparatus according to the present
invention comprises: an apparatus body having an
25 installation surface and a first surface opposite to
the installation surface; a holding portion provided at
the apparatus body, for detachably holding a radio

communication card which has a second surface and
an antenna provided on the second surface; and
a connecting portion arranged at the apparatus body,
for data communication with the radio communication
5 card held by the holding portion. The holding portion
is arranged to hold the radio communication card in
a manner such that the first and second surfaces face
in the same direction.

Further, an electronic apparatus according to the
10 present invention comprises: an apparatus body having
an installation surface and a holding portion for
detachably holding a radio communication card including
an antenna; and a connecting portion provided at the
apparatus body, for data communication with the radio
15 communication card held by the holding portion. The
holding portion is arranged to holding the radio
communication card in a manner such that the antenna is
exposed outside of the apparatus body and situated
farther from the installation surface of the apparatus
20 body than a center of the apparatus body with respect
to the height direction of the apparatus body.

According to the electronic apparatus constructed
in this manner, the radio communication card can be
used for radio communication between some electronic
25 apparatuses. This electronic apparatus is a highly
versatile apparatus that can be wirelessly connected or
linked to various other apparatuses with ease.

Further, the antenna of the radio communication card can be kept off the installation surface, so that influences of a floor or wall surface upon radio waves can be reduced, and steady data communication can be ensured.

Another electronic apparatus according to the invention comprises a removable cover that covers the holding portion and the radio communication card set in the holding portion. Further, the cover is formed in a manner such that the attachment of the radio communication card can be visually recognized from the outside. According to this arrangement, the cover can prevent dirt, dust, etc. from getting into the holding portion. Since the inside of the holding portion can be visually observed through the cover, moreover, the attachment of the radio communication card can be easily recognized, so that wrong operation can be prevented.

Still another electronic apparatus according to the invention comprises a slide switch; a rotary switch; and setting means for setting operating states of the apparatus in accordance with combinations of shift positions of the slide and rotary switches. Since the operating modes are set by means of combinations of the slide and rotary switches only, the operating efficiency can be improved, and the switches can be reduced in number so that the apparatus is

miniaturized and its manufacturing cost is lowered.

A further electronic apparatus according to the invention uses a PC card as the radio communication card. With use of the standardized PC card as a radio communication module, the apparatus is highly versatile, and can be wirelessly connected or linked to various other apparatuses with ease.

Additional objects and advantages of the invention will be set forth in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention may be realized and obtained by means of the instrumentalities and combinations particularly pointed out hereinafter.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate presently preferred embodiments of the invention, and together with the general description given above and the detailed description of the preferred embodiments given below, serve to explain the principles of the invention.

FIG. 1 is a perspective view schematically showing an outline of a radio communication system with an access point according to an embodiment of the present invention;

FIG. 2 is an exploded perspective view showing

the access point, a BT-PC card, and a cover;

FIG. 3 is a perspective view showing the access point in its vertical position;

FIG. 4 is a perspective view showing the rear side
5 of the access point;

FIG. 5 is a perspective view showing the access point in its horizontal position;

FIG. 6 is a perspective view showing the bottom side of the access point;

FIG. 7 is a perspective view showing the BT-PC
10 card;

FIG. 8 is an exploded perspective view showing the BT-PC card;

FIG. 9 is an exploded perspective view showing
15 the internal structure of the access point;

FIG. 10 is a perspective view showing a card slot of the access point;

FIG. 11 is a perspective view showing a connecting portion between the BT-PC card and a connector on
20 the card-slot side;

FIG. 12 is a front view showing the BT-PC card set in position;

FIG. 13 is a diagram showing the relationship between the minimum distance d and an attenuate level
25 of the radio wave output;

FIG. 14 is a front view showing the access point in its horizontal position;

FIG. 15 is a block diagram schematically showing the respective configurations of the access point and the BT-PC card;

FIG. 16 is a block diagram schematically showing the respective configurations of the BT-PC card and a personal computer for data communication with the access point; and

FIG. 17 is a table showing assignment of switch shift positions of the access point to operating states.

DETAILED DESCRIPTION OF THE INVENTION

An electronic apparatus (hereinafter referred to as access point) for radio communication connection according to an embodiment of the present invention will now be described in detail with reference to the accompanying drawings.

FIG. 1 shows a system for radio communication between an access point 10 according to the present embodiment and two personal computers 100. The access point 10 and each personal computer 100 are each detachably fitted with a PC card (hereinafter referred to as BT-PC card) 20 based on the radio communication standards called Bluetooth (hereinafter referred to as BT), for use as a radio communication card, which will be mentioned later. The access point 10, which is connected to a public data network by means of a modular cable 12, transfers data wirelessly

transmitted from the personal computers 100 to the public data network and wirelessly transmits data from the public data network to the personal computers by utilizing the BT-PC card 20.

5 As shown in FIGS. 2 to 6, the access point 10 is provided with a substantially rectangular apparatus body 14 that is formed of, for example, a synthetic resin. The apparatus body 14 has a slightly curved front face 14a, a substantially flat back face 14b
10 opposed to the front face, a pair of opposite side faces 14c, a top face 14d, and a bottom face 14e. The bottom and back faces 14e and 14b of the apparatus body 14 constitute first and second installation surfaces, respectively.

15 The apparatus body 14 of the access point 10 can be used in a vertical position such that the bottom face 14e is put on the top of a desk or the like, as shown in FIGS. 3 and 4. Alternatively, it can be used in a horizontal position such that the back face 14b is
20 put on the top of a desk or the like, as shown in FIG. 5. The back face 14b is formed having two engaging recesses 16 for pins, hooks, etc. By using these engaging recesses 16, the apparatus body 14 can be also used as of a wall-mounted type such that its
25 back face is opposed to a wall.

 A power switch 18 of a push-button type is provided on the one side face 14c of the apparatus

body 14. An RS232C connector 22 and an AC adapter terminal 23 for power connection are arranged on the other side face 14c. Further, a plurality of LED's 24 for use as display elements that indicate operating
5 states of the access point 10 are arranged side by side on the front face 14a of the apparatus body 14. The operating states include, for example, a power-on state (POWER), sending state (SD), receiving state (RD), off-hook state (OH), standby/active state
10 (STB/ACT) of the BT-PC card 20 (mentioned later), etc.

The top face 14d of the apparatus body 14 is provided with a card loading aperture 28 of a card slot 26 (mentioned later) and an ejector button 30. As seen from FIG. 6, moreover, the bottom face 14e is provided
15 with two modular jacks 32, which can be connected with the modular cable 12 for connecting the access point 10 to the public data network, a pair of slide switches 34a and 34b, left and right, and a rotary switch 35.

A skirt portion 36 is set up along the peripheral
20 edge portion of the bottom face 14e, and a notch 37 is formed in a part of the skirt portion 36. The skirt portion 36 serves as a leg portion when the apparatus body 14 is used in the vertical position. The modular cable 12 that is connected to the modular jacks 32 is
25 drawn out through the notch 37. Even in the case where the apparatus body 14 is used in the vertical position with the modular cable 12 connected to the modular

jacks 32, therefore, the apparatus body 14 can be steadily supported by means of the skirt portion 36 without being hindered by the modular cable.

The card slot 26 for use as a holding portion is located in the apparatus body 14. The card loading aperture 28 of the card slot 26 opens in the top face 14d of the apparatus body. The BT-PC card 20 can be detachably fitted to the card slot 26 through the card loading aperture 28.

The following is a detailed description of the BT-PC card 20 and the card slot 26. As shown in FIGS. 7 and 8, the BT-PC card 20 includes a card body 40 based on the PCMCIA standards, and an a transmitter-receiver portion 42 protruding from one end of the card body and based on the BT standards. The card body 40 has a substantially rectangular plastic frame 43, which supports the peripheral edge portion of a rectangular card substrate 44. A connector 45 is attached to one end of the card substrate 44, and the other end portion of the card substrate projects from the card body 40.

A plurality of electronic components 46 are mounted on one surface of the card substrate 44, that is, an upper surface 44a in this case. Arranged on the upper surface of the other end portion of the card substrate 44, moreover, are an antenna element 46, an LED 47 that glows when signals are transmitted or

received, and a headset portion 48 to be connected with a headphone, microphone, etc. which constitute the transmitter-receiver portion 42

5 The upper and lower surfaces of the card substrate
44, except the other end portions thereof, are covered,
respectively, by means of a pair of metallic covers 50a
and 50b that are fitted on the frame 43. Further, the
transmitter-receiver portion 42 has a plastic cap 51,
which is fitted on the other end of the card body 40
10 and covers the other end portion of the card substrate
44 and the antenna element 46, LED 47, and headset
portion 48 that are mounted on the upper surface of the
other end portion of the substrate 44.

15 The end of the BT-PC card 20 to which the
connector 45 is attached is a loading-side end for the
card slot 26. The front end of one side wall of the
frame 43 is formed having a first guide groove 52a,
which opens in the top face, one side face, and front
end face of the card body 40. The front end of the
20 other side wall of the frame 43 is formed having a
second guide groove 52b, which opens only in the other
side face and front end face of the card body 40. As
mentioned later, the first and second guide grooves 52a
and 52b serve to regulate the facing of the BT-PC card
25 20 as the card 20 is loaded into the card slot 26.

As shown in FIGS. 9 and 10, on the other hand, a
metallic frame 54 is provided in the apparatus body 14.

The frame 54 is fitted with the aforesaid power switch 18, RS232C connector 22, AC adapter terminal 23, etc. and various electronic components mentioned later. The metallic frame 54 includes a substantially flat shielding plate 56 that is situated adjacent and opposite the front face 14a of the apparatus body 14. A top center portion 56a of the shielding plate 56 extends close to the card loading aperture 28. The card slot 26 is located inside the shielding plate 56.

The card slot 26 includes a metallic holding frame 58 that is fixed to the shielding plate 56. The frame 58 is shaped and sized corresponding to the card body 40 of the BT-PC card 20 and opposed to the card loading aperture 28. Further, the card slot 26 includes a connector 60 on the tail end portion of the holding frame 58 and an ejector lever 61 on a side portion of the frame 58. The ejector button 30 is coupled to the lever 61. The connector 60 constitutes a terminal portion according to the present invention.

If the BT-PC card 20 is inserted into the card slot 26 through the card loading aperture 28, it is guided by the holding frame 58 so that its connector 45 is connected to the connector 60 of the card slot. The card body 40 of the BT-PC card 20 is held in the card slot 26 by means of the holding frame 58 and the connectors 45 and 60 that are connected to each other, and is connected electrically to the access point 10.

As shown in FIG. 11, plastic guide frames 65 are provided individually on the opposite end portions of the connector 60. The frames 65 are formed having first and second guide projections 62a and 62b
5 corresponding to the first and second guide grooves 52a and 52b of the BT-PC card 20, respectively. More specifically, the first guide projection 62a is shaped and positioned so that it can engage only the first guide groove 52a of the BT-PC card 20, while the second
10 guide projection 62b is shaped and positioned so that it can engage only the second guide groove 52b of the card 20.

Thus, the first and second guide grooves 52a and 52b can engage the first and second guide
15 projections 62a and 62b of the card slot 26, respectively, to set the BT-PC card 20 in a given position only when the card 20 is inserted into the slot 26 in a manner such that the grooves 52a and 52b are opposed to their corresponding projections 62a and
20 62b, that is, the upper surface (on the side of the metallic cover 50a) of the card 20 faces the front face 14a of the apparatus body 14.

If the BT-PC card 20 is inserted inside out into the card slot 26, the first and second guide grooves
25 52a and 52b never engage their corresponding guide projections 62a and 62b, so that attachment is restrained, that is, wrong attachment can be prevented.

In removing the BT-PC card 20, the ejector button 30 is depressed so that the ejector lever 61 presses the distal end face of the card 20. In consequence, the connectors 45 and 60 are disconnected from each other, and the card body 40 is pushed out toward the card loading aperture 28, whereupon the removal of the card 20 is allowed.

When the BT-PC card 20 is set in the card slot 26, only the card body 40 is held in the card slot, and the transmitter-receiver portion 42 is left exposed to the outside, as shown in FIG. 5, for example. Further, the card slot 26 is designed so that a minimum distance d between the top center portion 56a of the shielding plate 56 on the side of the apparatus body 14 and the transmitter-receiver portion 42 of the BT-PC card 20 is 1 mm or more, and preferably, 2 mm or more, with the card 20 set in position, as shown in FIG. 12.

In this set state, the transmitter-receiver portion 42 of the BT-PC card 20 is exposed, the minimum distance d from the shielding plate 56 is adjusted to 1 mm or more. By doing this, steady data communication can be effected without allowing the apparatus body 14 or shielding plate 56 to intercept or attenuate radio waves during data transmission or reception.

FIG. 13 shows the relationship between the distance d and an attenuate level of the radio wave output. As clearly understood from FIG. 13, if

the minimum distance d is adjusted to 1 mm or more, intercept and attenuate of radio waves by the shielding plate 56 can be prevented.

Further, the card slot 26 is designed so that the
5 transmitter-receiver portion 42 of the BT-PC card 20,
especially the antenna element 46, is located
eccentrically to the installation surface and situated
above a central position in the height direction of the
apparatus body 14 without regard to the working
10 position, vertical or horizontal, of the apparatus body
when the card 20 is set in position.

More specifically, in the case where the apparatus
body 14 is used in its vertical position with its
bottom face 14e serving as the installation surface, as
15 shown in FIG. 4, the transmitter-receiver portion 42
of the BT-PC card 20 in the card slot 26 is situated
above a center line A in the height direction of the
apparatus body, that is, in the direction perpendicular
to the installation surface. In the case where the
20 apparatus body 14 is used in its horizontal position
with its back face 14b serving as the installation
surface, as shown in FIG. 14, the transmitter-receiver
portion 42 of the BT-PC card 20 is situated farther
from the installation surface than a center line B in
25 the height direction of the apparatus body that is
perpendicular to the installation surface is, that is,
above the center line B.

Thus, the antenna element 46 of the BT-PC card 20 can be located off a desk top, wall, or the like without regard to the working position, vertical or horizontal, of the apparatus body, so that bad influences of the desk top or wall upon the radio waves that are transferred through the antenna element 46 can be lessened. At the same time, the BT-PC card 20 can be loaded into the card slot 26 only when its upper surface or the upper surface 44a of card substrate 44 on which the antenna element 46 is mounted faces the front face 14a of the apparatus body 14, as mentioned before. In the case where the apparatus body 14 is used in the horizontal position shown in FIG. 14, the antenna element 46 is always situated on the side remoter from the installation surface. Accordingly, the bad influences of the desk top or wall upon the radio waves can be further lessened. Thus, steadier data communication can be ensured.

In the case where the apparatus body 14 is used in the vertical position, the top face 14d that has the card loading aperture 28 extends substantially parallel to the bottom face 14e that serves as the installation surface, so that dirt, dust, etc. may possibly get into the apparatus body through the aperture 28. As shown in FIGS. 2 and 3, therefore, the access point 10 is provided with a cover 63 that can be removably fitted on the top face 14d of the apparatus body 14.

The cover 63 is formed of a nonmetallic material that transmits light, e.g., a transparent resin. In the case where the apparatus body 14 is used in the vertical position, the cover 63 on its top face 14d serves to cover the card loading aperture 28 of the card slot 26 and the BT-PC card 20 therein, thereby preventing dirt, dust, etc. from getting into the apparatus body.

Since the cover 63 transmits light, moreover, the attachment of the BT-PC card 20 can be externally visually recognized with ease, and the glowing state or active state of the LED 47 on the card 20 can be visually recognize from the outside.

The following is a description of the respective internal structures of the access point 10 and the BT-PC card 20 described above. As shown in FIG. 15, the access point 10 includes a CPU 72 for controlling the operation of the entire access point. The CPU 72 is connected with the LED's 24, slide switches 34a and 34b, rotary switch 35, and connector 60 as an interface connector. A main memory 74 and a ROM 76 are connected to the CPU 72 by means of a memory bus, and power supplied from the AC adapter terminal 23 is supplied to the CPU through a power supply element 77. The CPU 72 functions also as setting means according to this invention.

Further, the access point 10 includes a modem

element 70 that is connected to the public data network by means of the modular cable 12 and the modular jack 32. The modem element 70 and the RS232C connector 22 are connected to the CPU 72 through a changeover switch 78. The modem element 70 and the ejector button 30 function as a transmitter-receiver portion.

The main memory 74, which is composed of a plurality of DRAM's, is a memory device that is loaded with driver software including operating programs for the access point 10, a device driver, and a radio communication protocol. The ROM 76 is loaded with communication protocols for radio communication and the public data network.

The modem element 70 converts digital data received from the BT-PC card 20 into analog data, transfers the data to the public data network through the modular jack 32, converts the analog data received from the public data network through the modular jack 32 into digital data, and transfers the data to the CPU 72.

The RS232C connector 22 is provided for the serial connection between the access point 10 and other electronic apparatuses such as the personal computers 100 by means of a RS232C cable (not shown). For example, an ISDN terminal adapter may be connected to the access point 10 by means of the RS232C connector 22 and the RS232C cable so that the digital data received

from the BT-PC card 20 can be transferred directly.
Further, the access point 10 and the personal computers
100 may be connected to one another by means of the
RS232C connector 22 and the RS232C cable so that the
5 operating states (mentioned later) of the access point
10 can be set by means of the personal computers.

The changeover switch 78 serves for switching
between the connection with the public data network by
means of the modem element 70 and the modular jack 32
10 and the connection with the other electronic apparatus
by means of the RS232C connector 22.

On the other hand, the BT-PC card 20, as a radio
module based on the BT standards, comprises the antenna
element 46, an RF element 80, a base band element 81,
15 a memory 82, a crystal oscillator element 83, the
headset portion 48, an AD/DA converter element 84, and
the LED 47.

The connector 45 as an interface connector is used
for data transfer between the BT-PC card 20 and the
20 access point 10. The antenna element 46 transmits and
receives radio waves to execute radio communication,
and its working frequency band ranges from 2.4 to
2.5 GHz. The RF element 80 carries out signal
processing such that communication can be executed with
25 given working radio frequencies.

The base band element 81 digitally processes data
inputted through the antenna element 46 and the RF

element 80, converts them into data that can be processed in the access point 10 and loads them into the memory 82. The data are transferred to and from the access point. The LED 47 glows when the data are
5 transmitted or received, for example. The memory 82 is loaded with a radio protocol.

The crystal oscillator element 83 supplies reference waves that are used in the RF element 80. The headset portion 48 is connected with a headset that
10 includes the headphone and the microphone, and inputs and outputs aural signals. Further, the AD/DA converter element 84 converts analog data received from the headset portion 48 into digital data signals, converts digital data that are received from the access
15 point 10 through the base band element 81 into analog signals, and transmits the analog signals to the headset portion 48.

As shown in FIGS. 1 and 16, on the other hand, each personal computer 100 that performs radio
20 communication with the access point 10 comprises a body 114 that is furnished with a keyboard 112 and an openable liquid crystal display panel 116 on the body. The body 114 is provided with a card slot 118, which is removably loaded with another BT-PC card 20. The slot
25 118 is constructed substantially in the same manner as the card slot 26 of the access point 10, and the BT-PC card 20 is of the same type as the aforesaid one.

Further, the personal computer 100 comprises an interface connector 120 based on the PCMCIA standards and used to transfer data to and from the BT-PC card 20, a MPU 122 for controlling the operations of the connector 120 and the whole computer, and a USB 124 that serves as an interface for function expansion. The USB 124 is used for serial connection to the access point 10 by means of the RS232C connector 22, for example.

According to the access point 10 constructed in this manner, data are transferred between the BT-PC card 20 in the access point and the BT-PC card 20 in the personal computer 100, whereby radio communication of data can be effected between the access point 10 and the personal computer 100 and between a plurality of personal computers 100. If the access point 10 is connected to the public data network by means of the modular cable 12, data wirelessly transmitted from each personal computer 100 can be transferred to the public data network, and data received from the public data network can be wirelessly transmitted to each personal computer 100. Accordingly, there is no need of any cables for connecting the personal computers 100 or modular cables for connecting the computers 100 and the public data network, so that troublesome wire connection and arrangement can be eliminated. Thus, places for the installation of the personal computers

100 can be selected freely, the range of service can be extended, and the operating efficiency can be improved considerably.

5 According to the access point constructed in this manner, a radio communication card, especially a BT-PC card, is used as a radio module, so that the access point 10 can be improved in versatility and can be wirelessly connected or linked to various apparatuses with ease.

10 According to the access point described above, moreover, the radio communication card can be used without being influenced by metallic frames that are attached to the apparatus body 14, and a satisfactory distance is secured between the installation surface
15 and the antenna element to ensure steady data communication.

According to the access point 10, as shown in FIG. 6, on the other hand, various operating states of the access point can be set by a user or at the time of
20 shipment or an operator's inspection or maintenance operation in a manner such that shift positions of the slide switches 34a and 34b and the rotary switch 35 on the bottom face 14e of the apparatus body 14 are combined variously.

25 More specifically, each of the slide switches 34a and 34b are can be shifted between two positions L and H, and the rotary switch 35 between ten positions 0

to 9. As shown in FIG. 17, combinations of the shift positions of these switches are assigned individually to predetermined operating states.

Among these operating states, items that are
5 frequently reset by the user, e.g., normal (MODEM), normal (TA), maintenance (MODEM), and maintenance (CPU), can be set alternatively by changing only the respective shift positions of the slide switches 34a and 34b without shifting the rotary switch 35.
10 Thus, the user can easily set these operating states. In the operating state, maintenance (CPU), the PIN code of a BT system can be changed by input operation through the personal computer 100 with the access point 10 and the personal computer connected to each other by
15 means of the RS232C cable.

Further, items related to maintenance and items that are set at the time of shipment are assigned to the operating states that are set by shifting the slide switches 34a and 34b and the rotary switch 35, and the
20 operating states are reset by the operator.

In the access point 10, operating state data that are assigned to the combinations of the respective shift positions of the individual switches are stored in the main memory 74, and the CPU 72 sets the
25 corresponding operating states according to the shift positions of the slide switches 34a and 34b and the rotary switch 35 and the operating state data stored in

the main memory.

Thus, the various operating states can be set by shifting only the pair of slide switches 34a and 34b and the one rotary switch 35, so that the operating efficiency can be improved, and the switches can be reduced in number to lower the manufacturing cost. The operating efficiency can be further improved, in particular, since the operating states that are usually frequently reset by the user can be set by shifting the slide switches only.

The present invention is not limited to the embodiment described above, and various changes and modifications may be effected therein by one skilled in the art without departing from the scope or spirit of the invention. According to the foregoing embodiment, for example, the access point is connected to the public data network by means of the transmitter-receiver portion that includes the modular jack and the modem element. However, the object of connection of the access point is not limited to the public data network. More specifically, the access point may be connected to another electronic apparatus so that data can be transferred between the alternative apparatus and each personal computer 100 by radio communication. In this case, the transmitter-receiver portion may be omitted.

Additional advantages and modifications will

readily occur to those skilled in the art. Therefore,
the invention in its broader aspects is not limited to
the specific details and representative embodiments
shown and described herein. Accordingly, various
5 modifications may be made without departing from the
spirit or scope of the general inventive concept as
defined by the appended claims and their equivalents.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2